

## EP6000-EN1

Article code: SA0950590



**Europower standard, EN1 and EN2 generating sets with Honda air-cooled gasoline engine, 3000rpm, 50Hz, 4 stroke**

### **Generator:**

kVA max.:	6
kVA cont.:	5.4
kVA:	5.4kVA @ 1~230V
Amps cont.:	23A @ 1~230V
Dimensions l x w x h:	83x51x56cm
Weight incl. oil (+ coolant if water-cooled), excl. fuel:	75kg
Weight incl. oil (+ coolant if water-cooled) + fuel:	80kg

### **Engine:**

<b>Brand/Type:</b>	<b>Honda GX390 T2-VSP*</b>
HP max.:	11.1
Power:	8.2kW max. (3000rpm), 1-cylinder Gasoline, Air-cooled
Displacement:	389cm <sup>3</sup>
Consumption @75% load:	2.4 litres/hour
Tank:	6.1 litres
Autonomy @75% load:	2.5 hours
Noise level:	75dB(A)@7m (*)
EU Emission norm:	Stage V
CO2 emission:	0 g/kWh

### **Alternator:**

<b>Brand/Type</b>	<b>Sincro EK2MCT - 6kVA 230V - brushless</b>
Nominal voltage:	1~230V
Frequency:	50Hz
Protection degree:	IP23

Generators with \* cannot be used outdoors in the EU. For applications of generating sets indoors, or if you want to integrate these generators in vehicles, please contact us.

**Version:**

- 2 sockets 230V - 16A
- Circuit breaker
- Frame
- Oil guard
- Recoil starter

www.EUROPOWERGenerators.com



Your **EUROPOWER** dealer